

Retail Tablet



User Manual



About This Guide

Thank you for purchasing an i DISPLAY product. We recommend reading this user guide carefully in order to achieve optimal pleasure and performance and to maximize the service life of this product.

This guide describes how to setup the Retail Tablet. This guide is intended for retail personnel, sales people and anyone who wants to set up the Retail Tablet in a retail environment.

- **Introducing the Retail Tablet XL**, page 7, introduces the Retail Tablet its and components
- **Getting Started**, page 10, describes how to set up and start the Retail Tablet.
- **Playing Content**, page 14, describes the various options for displaying videos, pictures and applications on the Retail Tablet.
- **Main Android OS screen (Home screen)**, page 18, describes the Retail Tablet Home screen and Application Drawer, which provides access to tablet settings and other standard Android tools.
- **Retail Tablet Accessories**, page 20, describes the mounting attachments and other accessories that can be connected to the Retail Tablet.

You may also refer to

<http://www.i-display.com/products/retail-tablet-xl-technical-specification> to download the latest Retail Tablet specification sheet to download the latest version of this user guide. For support contact: support@i-display.com.

Important Notice

Copyright © 2012 Outform Ltd. All rights reserved.

All intellectual property rights in this publication are owned by Outform and protected by applicable copyright laws and international treaty provisions. Outform retains all rights not expressly granted. No part of this publication may be reproduced in any form whatsoever or used to make any derivative work without prior written approval by Outform.

Outform reserves the right to revise this publication, and/or make improvements or changes in the product(s) and/or the program(s) described in this documentation at any time without prior notice. The information in this document is provided in good faith, but without any representation or warranty whatsoever, whether it is accurate, or complete or otherwise, and on express understanding that i Outform shall have no liability whatsoever to other parties in any way arising from or relating to the information or its use.

All other trademarks are the property of their respective owners. Other company and brand products and service names are trademarks or registered trademarks of their respective holders.


 This device complies with CE/FCC regulations.

Index


Safety and Warnings	6
Introducing the Retail Tablet XL	7
Getting Started	10
Playing Content	14
Main Android OS Screen (Home Screen)	18
Retail Tablet Accessories	20

Safety and Warnings


NOTE

-  This mark is applied to indicate that the equipment conforms to European safety and electro-magnetic compatibility standards.


WARNING!

-  Main Supply: This equipment is designed to operate from a 100-240 Volt, 50/60Hz AC main supply. The use of other power sources may damage this equipment. Check that the voltage marked on the rating plate located at the rear of the power adaptor states 100-240V. The manufacturer will NOT accept responsibility for damage or injury caused by connecting to the wrong voltage.


WARNING!

-  Main Adaptor: The supplied power adaptor is compatible with a standard main socket. NB. If the power adaptor or lead gets damaged, it must be replaced by a qualified service agent with an approved adaptor of the same type and rating.

WARNING!

-  Dangerous voltage constituting a risk of electric shock is present inside this equipment.

WARNINGS!

-  The main plug shall be the main disconnect device and shall remain operable at all times.

Do not push objects into holes and ventilation slots.

Do not expose this product to dripping or splashing or place any objects filled with liquids on or near the product.

Do not place a naked flame source, such as lighted candles, on or near this product.

Do not attempt to repair this product yourself. Always use a qualified service agent to perform adjustments or repairs.

Introducing the Retail Tablet XL

This chapter introduces the Retail Tablet and its components.

What is the Retail Tablet?

The Retail Tablet is an Android-based (Android OS 2.3), interactive digital display that is specifically designed to be used by the retail market. The Retail Tablet is a robust, yet slim line unit that features a multi-touch screen, front camera and embedded Wi-Fi . Retail Tablet features include content auto-play, auto-copy and auto-detect features. The Retail Tablet comes in the following sizes: 7", 10" 15.6", 18.5" and 21.5".


You may refer to the www.i-DISPLAY.com for more information.

Retail Tablet Components

The following components are provided with the Retail Tablet:

Retail Tablet
Power Supply Unit





No.	Description
1.	Multi-Touch Screen with embedded Wi-Fi
2.	Power Indicator
3.	Bracket Screws for Attaching Multiple VESA Options
4.	Home Button (Back)
5.	USB Port
6.	Micro SD port for playing content
7.	USB Port
8.	PB-Molex connector for Connect Box. A Connect box has up to 12 buttons (push or touch) and one motion sensor.
9.	DC In – Power Input
10.	HDMI port for connecting the tablet to a larger screen
11.	SIM Card Port (optional)
12.	Headphones
13.	RS232 Connector
14.	Volume Control
15.	Brightness Control
16.	On/Off Button

Getting Started

This chapter describes how to set up and start the Retail Tablet.

Setting Up the Retail Tablet

To set up the Retail Tablet:

1. Remove the transparent cover sheet protecting the tablet's screen.
2. Use the fleece side of the provided cleaning cloth to clean off any dust on the touch screen.
3. Mount or position the tablet on the table, counter, shelf or floor according to the provided accessories. You may refer to the Retail Tablet Accessories section (page 20) for a description of mounting accessories and other devices that can be connected to the Retail Tablet

Turning On the Retail Tablet

The Retail Tablet is preconfigured to automatically start its Autoplay application when it is turned on. You may refer to the Logging Out of the Retail Tablet Autoplay Application section on page 11 for instructions on logging out of the i DISPLAY Autoplay application in order to access a standard Android OS screen

To turn on the Retail Tablet:

1. Connect one side of the power supply to the tablet's DC In socket located on its back lower side.
2. Plug the power supply into a standard electrical outlet. If this is the first time the tablet is turned on, then wait two minutes after plugging in the power supply before pressing the On/Off button to turn on the tablet.
3. Slide the On/Off button on the back of the tablet.

NOTE

Each time the tablet is powered on (after being off), it may take up to two minutes to begin to play.

4. The tablet is provided with a preloaded demonstration application that it automatically starts to play.

Logging Out of the Retail Tablet Autoplay Application

The Retail Tablet is preconfigured to automatically start its Autoplay application when it is turned on. The following describes how to log out of the i DISPLAY Autoplay application in order to go to a standard Android OS screen.

To access the Android OS screen:

1. While content is playing, quickly press the Home button (for one second). A password window is displayed, as shown below:



Please input password

OK Cancel

2. Tap in the white field to display a virtual keyboard.
3. Type in the password. If this is the first time you are using the Retail Tablet, then the password is: 11223344.
4. Tap the Done button and then the OK button. The following window is displayed




Hint

Please select set password or exit.

Set Password Exit

5. Tap the Exit button to exit the Autoplay application and to display the Android OS main screen.
– OR –
Tap the Set password button to enter a new password.
6. Enter the password twice (once in each field) and tap the OK button. A success message is then displayed. Tap the OK button.
Starts to play the content of Folder 0. If you change the password, please make sure to write it down and remember it. If you forget your password, then you must contact i Display for a new password.

A standard Android Home screen is then displayed, as shown below:



By default, the Retail Tablet is password protected in order to ensure that only authorized retail personnel can modify and configure it, as described below. You have the option to disable/enable the requirement to enter a password using the Enable/Disable Password.

To turn off the Retail Tablet:

Slide the On/Off button on the back of the tablet.

Playing Content

This chapter describes the various options for displaying videos, pictures and applications on the Retail Tablet.

What Does the Tablet Play?

The Retail Tablet runs standard Android applications (apk) using Android OS 2.3.

Video Formats: The Retail Tablet plays the following video formats:

- MPEG1 / MPEG2 / MPEG4
- Divx4 / Divx5 / Divx6
- H.264
- AVI

Image Formats: The Retail Tablet displays the following image formats:

- JPG
- BMP
- PNG
- GIF

You may refer to the

<http://www.i-display.com/products/retail-tablet-xl-technical-specification>
to download the latest Retail Tablet specification sheet.

How Does the Tablet Play?

The following describes the various options for displaying videos, pictures and applications (Android apk) on the Retail Tablet.

Default AutoPlay – Folder 0

The Retail Tablet disk drive contains a Root folder that can contain sub-folders. By default, the tablet plays the content of a folder named 0. This folder is located in the Root folder.

If Folder 0 contains multiple content files, then each is played one after the other in the order in which they were added to the Retail Tablet.

- **Video files** are played one after another.
- **Image files** are each displayed for three seconds.
- **Applications** continue running until there has been no user interaction for over three minutes or if you exit the application by quickly pressing the Home button. If you place an application in Folder 0, then it should be the only file in that folder.

For example, if a folder contains an image file and two video files in the following

order:

car-choice-banner.jpg

- car-choice-banner.mpeg
 - top-of-range.mpeg
 - then the tablet will first display the car-choice-banner.jpg image for three seconds, and then play the discount-car.mpeg video and then play the top-of-range.mpeg video.
- The tablet will then repeatedly play this sequence in a loop.

Connect Box – Selecting Folders 1 – 12

The Retail Tablet can also play the content of folders named from 1 to 12 if a Connect Box is connected to it. This Connect Box has 12 connectors for push buttons or touch sensors and 1 connector for motion sensor.

The Retail Tablet plays the content of Folder 0 by default. If one of the Connect Box buttons is pressed, then the Retail Tablet plays the same numbered folder once.

After it finishes:

The content of Folder 0 will then play repeatedly.

- If button number 1 is pressed on the Connect Box, then the content of Folder 1 is played once and then the content of Folder 0 is played repeatedly.

Motion Sensor

The Retail Tablet can also have an additional connector for a motion sensor. The motion sensor enables the Retail Tablet to play the content of a folder named MS, as follows:

ON Mode

This option enables you to set up the Retail Tablet so that by default it plays the contents of Folder 0 until the sensor detects motion. Then the Retail Tablet automatically starts playing the content of the **MS** folder.

The content in the MS folder is played repeatedly as long as motion is detected.

When motion is no longer detected, the tablet goes back to playing the content of Folder 0 repeatedly. If the tablet is playing an application and it is not touched for more than three minutes, then it returns to playing the content of Folder 0 repeatedly.

You may refer to the

<http://www.i-display.com/products/retail-tablet-xl-technical-specification> to download the latest Retail Tablet specification sheet to download the latest Retail Tablet specification sheet.

Barcode Reader – Plays Per Barcode

The Retail Tablet can be used to automatically play the content of a specific file in the Root directory of the tablet when a barcode reader is connected.

Copy a file onto the Retail Tablet with the same exact name as the barcode. The tablet will then automatically play the content of that file when a product with that barcode is read.

How Do I Load Content?

Retail Tablet auto copy feature makes loading content simple!

You can load content files using either a USB drive, a Micro SD, Wi-Fi or a mobile network (using a SIM card), as follows.

USB – Loading Content

Loading Content into Folder 0

To load from a USB drive into Folder 0:

1. Create a folder named 0 on a USB disk. Remove all other content from the USB drive.

If a video or image is playing, then insert the USB drive into one of the two USB

2. ports on the back of the tablet.

If an application is playing, then insert the USB drive into one of the two USB ports on the back of the tablet and then after ten seconds, quickly press the Home button on the back of the tablet.

After a few seconds a window pops up requesting a password.

Enter the password and tap the OK button. If this is the first time you are using the

3. Retail Tablet, then the password is: 11223344. The following window is displayed:

Hint	
Folder 0 exists.	
Replace	Append

Tap the Replace button to delete the content of Folder 0 on the tablet and replace

4. it with the content of Folder 0 on the USB drive.

– OR –

Tap the Append button to add the content of Folder 0 on the USB drive to the content of Folder 0 on the tablet.

A success message is displayed after the content has been copied. The file(s) in Folder 0 will automatically start playing. If multiple files are in Folder 0, then they

5. play one after another repeatedly.

If the tablet does not start to play the content, then restart it and the content should start playing automatically after restart.

NOTE

Do not turn off the Retail Tablet or remove the USB drive while it is copying. We recommend removing the USB disk after its content has been successfully copied.

Loading Content into Other Folders

You can use the standard Android Explorer to copy folders/files to the tablet. For example, into the Folders 1 through 12, the MS folder or a file with the same name as a barcode.

Loading an Application

If one of the files that was copied to the Retail Tablet is an application (Android apk) then an installation wizard automatically starts,

1. Tap the Install button
2. Tap the Open or Done button to run the application.

Micro SD – Playing Content

A Micro SD card can be used to play content on the tablet. The Retail Tablet will then automatically start repeatedly playing the content on the Micro SD. This procedure does not affect the contents already on Folder 0 of the Retail Tablet, meaning that when you remove the Micro SD card, the tablet will go back to playing the content in Folder 0.

To play Micro SD content:

Insert the Micro SD card into the Micro SD port on the back of the tablet. A password window is automatically displayed.

The content of the Micro SD card will automatically play in a loop.

You must leave the Micro SD card inserted in the tablet as long as it is playing.

Browser and Market – Downloading Content


You can download content using Wi-Fi or mobile connection to the Root folder of the tablet and then move the content to Folder 0 (or Folders 1 through 12) using



Explorer which can be accessed from the Applications Drawer.

Main Android OS Screen (Home Screen)

Home Screen

While you navigate in the Android environment, you can return to this Home screen by tapping the Home  button.

The Home screen provides the following options:



Browser: Tap to open a standard web browser in which you can access the Internet and surf the web.



Applications: Tap to display the Applications Drawer which enables access to the applications and tools installed on the Retail Tablet. You may refer to the Applications Drawer section below for more information.

Applications Drawer

The Retail Tablet provides a standard Android Application Drawer which enables access to the applications and tools installed on the tablet. The following describes some that are especially relevant to the Retail Tablet.



Settings: Tap to configure Retail Tablet settings, such as Wi-Fi, Mobile and so on.



i Display: Tap to return to autoplaying the content of Folder 0 in a loop.




Explorer: Tap to open a standard file explorer window which you can use to transfer files to/from the Retail Tablet. This option is especially useful for transferring files downloaded from the Internet to Folder 0.



Market: Android Market is an online software store developed by Google for Android OS devices. You can use it to download applications to the Retail Tablet.

Settings

Tap the Settings  button to configure typical Android setting options. Take note of the following options that are particularly relevant for the Retail Tablet.

Setting Up Wireless Networks

You can tap the Settings Wireless & networks option to configure Wi-Fi and Mobile networks settings in order to download content to the Retail Tablet.

This menu also enables you to configure Bluetooth settings for working with Bluetooth accessories, such as Bluetooth earphones.

Display Brightness

We recommend setting the Retail Tablet screen to its maximum brightness, as follows.

Either:

Use the Brightness button on the back of the Retail Tablet

– OR –

Use the Settings --> Display --> Brightness option, which can be accessed from the Android OS screen.

Retail Tablet Accessories

This chapter describes the mounting attachments and other accessories that can be connected to the Retail Tablet.

Printer

The Retail Tablet supports standard Android OS 2.3 printer drivers. This enables the connection of a printer that can be used by the applications (apks) that you load, such as coupon printer.

Barcode Reader

The Retail Tablet can be used to automatically play the content of a specific folder by connecting a barcode reader. You can copy a folder onto the Retail Tablet that has the same name as the barcode. The tablet will then automatically play the content of that folder when a product with that barcode is read.

For example, If the barcode of a product is **12345678**, then a file named **12345678** can be placed in the Root folder of the Retail Tablet. The Retail Tablet will then play the file named **12345678** when the barcode reader scans the product barcode **12345678**.

Connect Box

The Retail Tablet can be connected to a Connect Box that has 12 push buttons or touch sensors. The Retail Tablet will then play the relevant folder according to which button is pressed, as described in the Connect Box – Selecting Folders 1 – 12 section on page 15.

This Connect Box can also have one motion sensor which enables the display of a folder named MS when motion is detected, as described on page 15.

Mounting Options

The following are some of the mounting options available from i-DISPLAY.

Fixed Shelf or Table Bracket



Rotating Shelf or Table Bracket



Counter Disp

Floor Display



Refer to www.i-display.com to download the latest product specification sheet

i DISPLAY

Interactive Digital Displays

For further information or support, please contact: support@i-display.com

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.